

Certificate of Conformity

No. ESY 086470 0225 Rev. 01

Holder of Certificate: **Ginlong Technologies Co., Ltd.**

No.57 Jintong Road
Binhai Industrial Park, Xiangshan
315712 Ningbo, Zhejiang
PEOPLE'S REPUBLIC OF CHINA

Product:

Converter
Hybrid Inverter

Model(s):

S6-EH1P3K-L-PLUS, S6-EH1P3.6K-L-PLUS, S6-EH1P4.6K-L-PLUS, S6-EH1P5K-L-PLUS, S6-EH1P6K-L-PLUS, S6-EH1P8K-L-PLUS, S6-EH1P3K-L-PLUS(21A), S6-EH1P3.6K-L-PLUS(21A), S6-EH1P4.6K-L-PLUS(21A), S6-EH1P5K-L-PLUS(21A), S6-EH1P6K-L-PLUS(21A), S6-EH1P8K-L-PLUS(21A), S6-EH1P9K-L-PLUS(21A), S6-EH1P10K-L-PLUS(21A).

Parameters:

See next pages.

Applicable standards:

EN 50549-1:2019
EN 50549-10:2022


This Certificate of Conformity confirms the compliance with the above listed standards on a voluntary basis. It refers only to the sample submitted to TÜV SÜD Product Service GmbH and does not certify the quality or safety of the serial products. It was issued according to TÜV SÜD Product Service certification program Photovoltaics and Grid Integration. For details see: www.tuvsud.com/ps-cert

Test report no.:

7040924037115-01

Date,

2025-08-07



(Zhengdong Ma)

Certificate of Conformity

No. ESY 086470 0225 Rev. 01

Models	S6-EH1P3K-L-PLUS	S6-EH1P3.6K-L-PLUS	S6-EH1P4.6K-L-PLUS
PV-Input:			
Max. input voltage	DC 500 V		
Mppt voltage range	DC 90 V, ..., 435 V		
Max. input current	AC 16/16 A	AC 16/16 A	AC 16/16 A
Isc PV (absolute maximum)	AC 20/20 A	AC 20/20 A	AC 20/20 A
Battery Input / Output:			
Battery Type	Li-ion/Lead-acid		
Battery Voltage range	DC 40, ..., 60 V		
Max. Charge / discharge current	DC 70 A/ 70 A	DC 80 A/ 80 A	DC 105 A/ 105 A
AC-Output (Grid side):			
Rated output voltage	1/N/PE AC 230 V		
Rated output frequency	50 Hz		
Max. /Rated apparent output power	3000 VA	3600 VA	4600 VA
Max. /Rated output current	AC 13.1 A	AC 15.7 A	AC 20 A
Power factor range	-0.8, ..., 1, ..., +0.8		

Models	S6-EH1P5K-L-PLUS	S6-EH1P6K-L-PLUS	S6-EH1P8K-L-PLUS
PV-Input:			
Max. input voltage	DC 500 V		
Mppt voltage range	DC 90 V, ..., 435 V		
Max. input current	AC 16/16 A	AC 16/16 A	AC 32/32 A
Isc PV (absolute maximum)	AC 20/20 A	AC 20/20 A	AC 40/40 A
Battery Input / Output:			
Battery Type	Li-ion/Lead-acid		
Battery Voltage range	DC 40, ..., 60 V		
Max. Charge / discharge current	DC 112 A/ 112 A	DC 135 A/ 135 A	DC 190 A/ 190 A
AC-Output (Grid side):			
Rated output voltage	1/N/PE AC 230 V		
Rated output frequency	50 Hz		
Max. /Rated apparent output power	5000 VA	6000 VA	8000 VA
Max. /Rated output current	AC 21.8 A	AC 26.1 A	AC 34.8 A
Power factor range	-0.8, ..., 1, ..., +0.8		

Certificate of Conformity

No. ESY 086470 0225 Rev. 01

Models	S6-EH1P3K-L-PLUS(21A)	S6-EH1P3.6K-L-PLUS(21A)	S6-EH1P4.6K-L-PLUS(21A)
PV-Input:			
Max. input voltage	DC 500 V		
Mpppt voltage range	DC 90 V, ..., 435 V		
Max. input current	AC 21/21 A		
Isc PV (absolute maximum)	AC 24/24 A		
Battery Input / Output:			
Battery Type	Li-ion/Lead-acid		
Battery Voltage range	DC 40, ..., 60 V		
Max. Charge / discharge current	DC 70 A/ 70 A	DC 80 A/ 80 A	DC 105 A/ 105 A
AC-Output (Grid side):			
Rated output voltage	1/N/PE AC 230 V		
Rated output frequency	50 Hz		
Max. /Rated apparent output power	3000 VA	3600 VA	4600 VA
Max. /Rated output current	AC 13.1 A	AC 15.7 A	AC 20 A
Power factor range	-0.8, ..., 1, ..., +0.8		

Models	S6-EH1P5K-L-PLUS(21A)	S6-EH1P6K-L-PLUS(21A)	S6-EH1P8K-L-PLUS(21A)
PV-Input:			
Max. input voltage	DC 500 V		
Mppt voltage range	DC 90 V, ..., 435 V		
Max. input current	AC 21/21 A		AC 42/42 A
Isc PV (absolute maximum)	AC 24/24 A		AC 48/48 A
Battery Input / Output:			
Battery Type	Li-ion/Lead-acid		
Battery Voltage range	DC 40, ..., 60 V		
Max. Charge / discharge current	DC 112 A/ 112 A	DC 135 A/ 135 A	DC 190 A/ 190 A
AC-Output (Grid side):			
Rated output voltage	1/N/PE AC 230 V		
Rated output frequency	50 Hz		
Max. /Rated apparent output power	5000 VA	6000 VA	8000 VA
Max. /Rated output current	AC 21.8 A	AC 26.1 A	AC 34.8 A
Power factor range	-0.8, ..., 1, ..., +0.8		

Certificate of Conformity

No. ESY 086470 0225 Rev. 01

Models	S6-EH1P9K-L-PLUS(21A)	S6-EH1P10K-L-PLUS(21A)
PV-Input:		
Max. input voltage	DC 500 V	
Mppt voltage range	DC 90 V, ..., 435 V	
Max. input current	AC 42/42 A	
Isc PV (absolute maximum)	AC 48/48 A	
Battery Input / Output:		
Battery Type	Li-ion/Lead-acid	
Battery Voltage range	DC 40, ..., 60 V	
Max. Charge / discharge current	DC 200 A/ 200 A	DC 210 A/ 210 A
AC-Output (Grid side):		
Rated output voltage	1/N/PE AC 230 V	
Rated output frequency	50 Hz	
Max. /Rated apparent output power	9000 VA	10000 VA
Max. /Rated output current	AC 39.1A	AC 43.5A
Power factor range	-0.8, ..., 1, ..., +0.8	

Certificate of Conformity

No. ESY 086470 0225 Rev. 01

Evaluated protection function and operational capabilities

Clause(s) / subclause(s) of EN 50549-1:2019	Applicable clause(s) / subclause (s) of this document	Remarks, optional modes and constraints	Verdict
4.4.2 Operating frequency range	5.2.1 Frequency operating range	--	Pass
4.4.3 Minimal requirement for active power delivery at underfrequency	5.2.1 Frequency operating range	--	Pass
4.4.4 Continuous operating voltage range	5.2.2 Voltage operating range	--	Pass
4.5.2 Rate of change of frequency (ROCOF) immunity	5.3.1 Immunity to disturbances – Rated of change of frequency (ROCOF)	--	Pass
4.5.3.2 Generating plant with non-synchronous generating technology	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	--	Pass
4.5.4 Over-voltage ride through (OVRT)	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	--	Pass
4.6.1 Power response to overfrequency	5.4 Active response to frequency deviation	--	Pass
4.6.2 Power response to underfrequency	5.4 Active response to frequency deviation	--	Pass
4.7.2.2 Voltage support by reactive power, Capabilities	5.5.1 Power capabilities assessment	--	Pass
4.7.2.3 Voltage support by reactive power, Control modes	5.5.2 Voltage support by reactive power - test to determine the reactive power control modes	Q setp. Q(U) Cos ϕ setp. Cos ϕ (P)	Pass
4.7.2.3.2 Set point control modes	5.5.2.3 Verification procedure for set point control	Q setp. Cos ϕ setp.	Pass
4.7.2.3.3 Voltage related control modes	5.5.2.5 Verification procedure for power related control modes for reactive power	Q(U)	Pass
4.7.2.3.4 Power related control mode	5.5.2.5 Verification procedure for power related control modes for reactive power	Cos ϕ (P)	Pass
4.7.3 Voltage related active power reduction	5.6 Voltage related active power reduction - P(U)	P(U)	Pass
4.7.4.2.2 Zero current mode for converter connected generating technology	5.3.3 Immunity to disturbances - Fault ride through, over-voltage (OVRT) and under-voltage (UVRT)	--	Pass
4.9.3 Requirements on voltage and frequency protection	5.8.3 Verification procedure for generating plants to be connected to a LV distribution network with Interface protection as internal device	--	Pass

Certificate of Conformity

No. ESY 086470 0225 Rev. 01

4.9.4 Means to detect island situation	5.8.6 Islanding detection	Active methods tested with a resonant circuit according to EN 62116	Pass
4.10.2 Automatic reconnection after tripping	5.9.3 Automatic reconnection after tripping	--	Pass
4.10.3 Starting to generate electrical power	5.9.4 Starting to generate electrical power	--	Pass
4.11.1 Ceasing active power	5.10 Active power reduction on set point	--	Pass
4.11.2 Reduction of active power on set point	5.10 Active power reduction on set point	--	Pass
4.12 Remote information exchange	5.11 Remote information exchange	Standardized communication protocol not provided by manufacturer	N/A
4.13 single fault tolerance of interface protection system and interface switch	5.12 Requirements regarding single fault tolerance of interface protection system and interface switch	--	Pass

Certificate of Conformity

No. ESY 086470 0225 Rev. 01

Evaluated parameter and parameter range

Specific technical requirement (e.g. grid codes)		EN 50549-1:2019			
Clause(s) / subclause(s) of EN 50549-1:2019	Parameter	Remarks/ additional information	Configurable value range	Default value	
4.4.2 Operating frequency range	47.0 – 47.5 Hz Duration	--	0 – 20 s	Unlimited with protection setting only	
	47.5 – 48.5 Hz Duration	--	30 – 90 min	Unlimited with protection setting only	
	48.5 – 49.0 Hz Duration	--	30 – 90 min	Unlimited	
	49.0 – 51.0 Hz Duration	--	not configurable	Unlimited	
	51.0 – 51.5 Hz Duration	--	30 – 90 min	Unlimited with protection setting only	
	51.5 – 52 Hz Duration	--	0 – 15 min	Unlimited with protection setting only	
4.4.3 Minimal requirement for active power delivery at underfrequency	Reduction threshold	--	not configurable	No reduction	
	Maximum reduction rate	--	not configurable	N/A	
4.4.4 Continuous operating voltage range	Upper limit	--	not configurable	110% U _n	
	Lower limit	--	not configurable	85% U _n	
4.5.2 Rate of change of frequency (ROCOF) immunity	ROCOF withstand capability (defined with a sliding measurement window of 500 ms)	--	not configurable	2 Hz/s	
4.5.3.2 Under-voltage ride through (UVRT) Generating plant with non-synchronous generating technology	Maximum power resumption time	--	not configurable	1 s	
	Voltage-Time-Diagram	--	See figure 6 default requirement curve of EN 50549-1:2019	Time [s]	U [p.u.]
				0.0	0.2
				0.15	0.2
4.5.4 Over-voltage ride through (OVRT)	Voltage-Time-Diagram	--	not configurable See figure 8 of EN 50549-1:2019	1.5	0.85
				Time [s]	U [p.u.]
				0.0	1.25
				0.1	1.25
				0.1	1.20
				5.0	1.20
				5.0	1.15
				60	1.15
				60	1.10
4.6.1 Power response to overfrequency	Threshold frequency f ₁	--	50.2 Hz – 52 Hz	50.2 Hz	

Certificate of Conformity

No. ESY 086470 0225 Rev. 01

	Droop	--	2 % – 12 %	5 %
	Power reference	--	P_M P_{max}	P_{max} for ESS
	Intentional delay	--	0 – 2 s	0s
	Deactivation threshold f_{stop}	--	50.0 Hz – f_1	deactivated
	Deactivation time t_{stop}	--	0 – 600 s	-
	Acceptance of staged disconnection	--	yes no	No
4.6.2 Power response to underfrequency	Threshold frequency f_1	--	49.8 Hz – 46 Hz	49.8 Hz
	Droop	--	2 – 12 %	5 %
	Power reference	--	P_M P_{max}	P_{max}
	Intentional delay	--	0 – 2 s	0 s
4.7.2.2 Voltage support by reactive power - Capabilities	Active factor / Reactive power (% P_d) range overexcited	--	0.8 – 1 / 60 % P_D – 0	0.9 – 1 / 48.4 % P_D – 0
	Active factor / Reactive power (% P_d) range underexcited	--	0.8 – 1 / 60 % P_D – 0	0.9 – 1 / 48.4 % P_D – 0
4.7.2.3 Voltage support by reactive power - Control modes	Enabled control mode	--	Q setp. Q(U) Cos φ setp. Cos φ (P)	Q setp.
4.7.2.3.2 Voltage support by reactive power - Setpoint control modes	Q setpoint and excitation	--	0 – 60 % P_D	0
	cos φ setpoint and excitation	--	1 – 0.8	1
4.7.2.3.3 Voltage support by reactive power - Voltage related control modes	Characteristic curve – Q (U)	--	--	Indicate default characteristic
	Point a	--	50% U_n – 100% U_n	93 % U_n
	Point b	--	50% U_n – 100% U_n	94 % U_n
	Point c	--	100% U_n – 120% U_n	106% U_n
	Point d	--	100% U_n – 120% U_n	108 % U_n
	Min. reactive power	--	0 – 60 % P_d (Q_{max} under)	48.4 % P_d
	Max. reactive power	--	0 – 60 % P_d (Q_{max} over)	48.4 % P_d
	Time constant	--	3 s – 60 s	3.0 s
	Min cos φ	--	0.0 – 1	0.4
	Lock in power	--	0 % – 20 %	20%
	Lock out power	--	0 % – 20 %	5%
4.7.2.3.4 Voltage support by reactive power - Power related control mode	Characteristic curve – Cos φ (P)	--	--	Indicate default characteristic
	Point a	--	0 – 100% P_n / PF:-0.8, ..., +0.8	15% P_n / PF=0.8
	Point b	--	0 – 100% P_n / PF:-0.8, ..., +0.8	20% P_n / PF=1
	Point c	--	0 – 100% P_n / PF:-0.8, ..., +0.8	80% P_n / PF=1

Certificate of Conformity

No. ESY 086470 0225 Rev. 01

	Point d	--	0 – 100%Pn/ PF:-0.8, ..., +0.8	90%Pn/ PF=-0.9
	Cos φ	--	0.8 – 1	0.8
	Time constant	--	3 s – 60 s	3.33 s
	Lock in voltage	--	105 %Un	deactivated
	Lock out voltage	--	100 %Un	deactivated
	4.7.3 Voltage related active power reduction	Characteristic curve - P (U)	--	Indicate default characteristic
	Point a	--	0 – 100%Pn/ U:0 V, ..., 264.5 V	100%Pn/ U=207 V
	Point b	--	0 – 100%Pn/ U:0 V, ..., 264.5 V	100%Pn/ U=230 V
	Point c	--	0 – 100%Pn/ U:0 V, ..., 264.5 V	100%Pn/ U=253 V
	Point d	--	0 – 100%Pn/ U:0 V, ..., 264.5 V	5%Pn/ U=257.6 V
	Time constant	--	3 s – 60 s	3.33 s
	4.7.4.2.2 Zero current mode for converter connected generating technology	Enabling	--	enable disable disabled
		Static voltage range overvoltage	--	100 %Un – 120 %Un 120 %Un
		Static voltage range undervoltage	--	20 %Un – 100 %Un 50 %Un
	4.9.3 Requirements on voltage and frequency protection	Threshold for protection as dedicated device [in A or kW. kVA]	--	16 A – 250 kVA Not specified, inverter integrated as default
		Undervoltage threshold stage 1	--	0.2 Un – 1 Un 0.85Un
		Undervoltage operate time stage 1	--	0.1 s – 100 s 100 s
		Undervoltage threshold stage 2	--	0.2 Un – 1 Un 0.5Un
		Undervoltage operate time stage 2	--	0.1 s – 5 s 5 s
		Overvoltage threshold stage 1	--	1.0 Un – 1.2 Un 1.2Un
		Overvoltage operate time stage 1	--	0.1 s – 100 s 100 s
		Overvoltage threshold stage 2	--	1.0 Un – 1.3 Un 1.3Un
		Overvoltage operate time stage 2	--	0.1 s – 5 s 5 s
		Overvoltage threshold 10 min mean protection	--	1.0 Un – 1.15 Un 1.1Un

Certificate of Conformity

No. ESY 086470 0225 Rev. 01

	Underfrequency threshold stage 1	--	47.0 Hz – 50.0 Hz	47.5 Hz
	Underfrequency operate time stage 1	--	0.1 s – 100 s	100 s
	Underfrequency threshold stage 2	--	47.0 Hz – 50.0 Hz	47 Hz
	Underfrequency operate time stage 2	--	0.1 s – 5 s	5 s
	Overfrequency threshold stage 1	--	50.0 Hz – 52.0 Hz	51.5 Hz
	Overfrequency operate time stage 1	--	0.1 s – 100 s	100 s
	Overfrequency threshold stage 2	--	50.0 Hz – 52.0 Hz	52 Hz
	Overfrequency operate time stage 2	--	0.1 s – 5 s	5 s
4.10.2 Automatic reconnection after tripping	Lower frequency	--	47.0 Hz – 50.0 Hz	49.5 Hz
	Upper frequency	--	50.0 Hz – 52.0 Hz	50.2 Hz
	Lower voltage	--	50 %U _n – 100 %U _n	85 %U _n
	Upper voltage	--	100 %U _n – 120 %U _n	110 %U _n
	Observation time	--	10 s – 600 s	60 s
	Active power increase gradient	--	5% – 3000%/min	10 %/min
4.10.3 Starting to generate electrical power	Lower frequency	--	47.0 Hz – 50.0 Hz	49.5 Hz
	Upper frequency	--	50.0 Hz – 52.0 Hz	50.1 Hz
	Lower voltage	--	50 %U _n – 100 %U _n	85 %U _n
	Upper voltage	--	100 %U _n – 120 %U _n	110 %U _n
	Observation time	--	10 s – 600 s	60 s
	Active power increase gradient	--	5% – 3000 %/min	disabled
4.11.1 Ceasing active power	Activation option	--	Can be achieved by Modbus communication protocol, APP or Solis cloud, acceptance should be made by the DSO and responsible party	
4.11.2 Reduction of active power on set point	Activation option	--	Can be achieved by Modbus communication protocol, APP or Solis cloud, acceptance should be made by the DSO and responsible party	
4.12 Remote information exchange	Available communication standards	--	Standardized communication protocol not provided by manufacturer	